

## FUD-3I/3U

### Three Phase Ac Current Voltage Transducer

Change the measured AC current/voltage to the DC current/voltage output according to the linear scale  
 Excellent temperature characteristic and good working stability  
 Configuration compactness and briefness

### Features

1. Three phase current / voltage transducer
2. AC current / voltage transducer
3. Accuracy class can reach 0.2%
4. AC input range can be customized
5. DC output range can be customized



### Parameters

Technical Index	
Standard	GB/T 13850-1998, IEC688:1992
Accuracy	0.2%, 0.5%
Consumption	≤3VA
Accuracy drift	Annual variation <0.2%
Insulation voltage	AC 2kV/min.1mA (Between input- output / power)
Insulation resistance	≥20MΩ (DC500V)
Surge voltage	5KV (Peak value), 1.2/50μs
Response time	≤350ms
Input range	AC 0-10A, AC 0-500V (Option), 50/60Hz
Absorbed power	<0.5VA/450V, <0.2VA/100V, <0.1VA/5A
Overload	Current: 2 times continuous, 30 times /1s;
Load resistance	Current output: RL ≤550Ω Voltage output: RL ≥2kΩ
Working environment	Temperature: -10 to +50°C RH: 20-90%, without condensation
Storage conditions	Temperature: -40 to +70°C RH: 20-95%, without condensation
Installation	35mm DIN sliding-way or M4 screws
Dimension	110mm x 75mm x 120mm

## Model Description

### FUD-Type-Input-Power Supply-Output

Type	3I: Three phase AC current transducer 3U: Three phase AC voltage transducer
AC input	A1: 0-1A, A2: 0-5A, A3: 0-10A. V0: 0-70V, V1: 0-120V, V2: 0-250V, V3: 0-300V, V4: 0-450V, V5: 0-500V.
Power supply	P1: AC110V±10%, P2: AC220V±15%, P3: AC110V-330V.
DC output	O1: 0-5V, O2: 1-5V, O3: 0-20mA, O4: 4-20mA, O5: RS485.

### Example 1: FUD-3I-A2-P2-O4

FUD series three phase AC current transducer	Input: AC 0-5A Power supply: AC220V±15% Output: DC4-20mA
--	--

### Example 2: FUD-3U-V2-P2-O4

FUD series three phase AC voltage transducer	Input: AC 0-250V Power supply: AC220V±15% Output: DC4-20mA
--	--

Please check the type, input range, output range and power supply when your order the product.