

TEST-200

200A PORTABLE PRIMARY CURRENT INJECTION TEST KIT

TEST-200 200A primary current injection test kit adopts 32bit ARM Chip to control its output process and large capacity of toroidal transformers. It is equipped with current meter; it can show primary current value, second current value, the action time and voltage value. Packing is used as aluminum alloy body with PC panel. LCD screen display single-phase protective relay test device of voltage and current output stopwatch; a full isolation, adjustable AC and DC voltage, AC direct current; an adjustable DC voltage and an adjustable AC voltage; output circuit with double overload protection, high output capacity, small size, light weight, high reliability. Primary Injection Kit Compact Model TEST-200 is designed to operate on single phase 230/240 Volts AC 50/60 Hz. to develop smooth & continuous test current. The test equipment gives high current output at low cost and with inherent safety at minimum precaution. TEST-200 is mainly applied to Circuit Breaker testing in the power system, contact resistance test and relay test.

Features

- 1. AC Voltage output up to 250V;
- 2. DC Voltage output up to 300V;
- 3. Max current output up to 250A;
- 4. Built-in digital timer resolution 1ms;
- 5. Thermal and short-circuit protection;
- 6. Permanent current up to 200 A, 2KVA;
- 7. Built-in digital ammeter 0.2% accuracy;
- 8. Small size, light weight, easy to test on-site;
- 9. Suite for all kinds of overcurrent relay testing;
- 10. Suite for all kinds of overvoltage relay testing;
- 11. With high precision 0.0000-99999S Stopwatch;
- 12. Current injection continuous output from 0-50A;
- 13. Have one channel DC Auxiliary Output from 0 to 220V;



Application

- 1. Switchgear Testing
- 3. Primary injection tests
- 5. Recloser and Sectionalizers

- 2. Ground Grid Testing
- 4. Protective Relay Testing
- 6. Micro Circuit Breaker Testing

Subject to change without notice



Parameters

Electrical parameters				
Accuracy	±0.5%			
Power Supply(AC)	220V±10%·2000VA, 50Hz/60Hz or			
	110V±10%·2000VA, 50Hz/60Hz			
Current Output (AC)	200A-5V or 100A-10V			
Capacity	2KVA			
The current output waveform distortion	≤5%			
Dual protection	overload electronic protection and software protection			
Primary current				
Range	0-250A			
Resolution	0.1A			
Accuracy	<0.5% RG			
AC Voltage Output				
Range	0-250V AC			
Resolution	0.1V			
Accuracy	<0.2% RG			
DC Voltage Output				
Range	0-300V DC			
Resolution	0.1V			
Accuracy	<0.5% RG			
Current Output duration				
200A range	200A 1-2minutes			
	100A 3-6minutes			
	50A Continuous			
10A range	10A Continuous			
Stopwatch				
Range	0.0000-99999S			
Resolution	0.1mS			
Accuracy	±5 words			
Max input voltage	DC 250V			
(With contact and potential input)				
Ammeter				
Range	Inside 0.000-250.0A			
	Outside 0.000-6.000A(AC or DC)			
Accuracy	<0.2%			
Voltmeter				
Range	0.0-600.0V(AC or DC)			
Accuracy	<0.2%			
Measuring mode	AC True RMS			
	DC Average value			



Main functions

MODEL	ACCURACY	PRIMARY CURRETNT	AMMETER (0-6A)	TIMER	POWER	INJECTION CURRENT TIME	DIMENSION(W×D×H) (mm)	WEIGHT	REMARK
TEST-200	0.5%	0-250A	YES	YES	2KVA	200A: 2-3min;100A:3-6min	340×270×250	22.5KG	Integrated structure
TEST-901	0.5%	0-1100A	YES	YES	5KVA	1000A: 2-3min;500A:3-6min	430×260×260	25KG	Integrated structure
TEST-902	0.5%	0-2200A	YES	YES	12KVA	2000A:2-3min;1000A:3-6min	360×300×295 and 320×300×300	35KG+15KG	Fission structure
TEST-903	0.5%	0-3300A	YES	YES	15KVA	3000A: 2-3min;1500A:3-6min	380×350×360 and 340×290×420	48KG+42KG	Fission structure
TEST-905	0.5%	0-5500A	YES	YES	25KVA	5000A:2-3min;2500A:3-6min	430×430×445 and 550×450×600	68KG+55KG	Fission structure